

FM Radio | Jobsite Radio | FM | Battery Powered / Mains Powered | Digital | 15 W | Screen size: 2.2 " | Blue White Screen | Bluetooth® | IPX5 | Carrying handle | Black / Yellow



Product specifications RDFM3100YW:

Antenna type	External
Battery play time	22 hrs
Bluetooth® version	4.2
Carrying handle	Yes
Colour	Black
	Yellow
Connection input	1x 3.5 mm
Depth	280.00 mm
Device power input connection(s)	DC Power Connector
Driver size	60 mm
FM frequency range	87.5 - 108 MHz
Fm preset stations	20
Height	198.00 mm
Input current	1.0 A
Input voltage	9 V DC
IP rating	IPX5
Material	ABS

	Rubber
Maximum transmit antenna gain	0 dBi
Maximum transmit power	-6 dBm
Media playback	AUX
	Radio
Power adapter cable length	1.50 m
Power cable side A	C7
Power cable side B	DC Power adapter
Power consumption in operating mode	8 W
Power consumption in standby mode	0 W
Power plug	Type C (CEE 7/16)
Power source type	Battery Powered
	Mains Powered

Radio design	Jobsite Radio
Radio type	FM Radio
Required batteries (not included)	6x C/LR14
Screen	Blue White Screen
Screen size	2.2 "
Shock protection	Yes
Speaker channels	Mono
Speaker peak power	15 W
Speaker RMS	5 W
Supported Bluetooth® profiles	A2DP
	AVRCP
Supported radio band	FM
Supported wireless technology	Bluetooth®
Transmit frequency range	2402 - 2480 MHz
Tuning type	Digital

Packaging information:

Brand	Nedis
Order code	RDFM3100YW
EAN single Product	5412810326266
EAN Inner Carton	
EAN Outer Carton	5412810384358
Packaging	Giftbox
Package contents	Jobsite radio
	Power cable

Read more online

Quantity	L x	W x	H (mm)	Weight
1	200 mm	330 mm	205 mm	2550 g
4	415 mm	350 mm	425 mm	10600 g

