



CABLESTAR 400

Stereo radio for unencrypted digital radio programs via cable

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588039438	schwarz	0000/3943	3.95 kg	3.05 kg	38.00 x 13.50 x 18.00 cm	48.00 x 18.50 x 21.50 cm

TOP FEATURES

Reception of unencrypted, digital radio programs via DVB-C

Top quality OLED display

Time display

Save up to 20 of your favorite stations

2 x 10 W stereo system powered by ELAC

AMBIENT OPERATING CONDITIONS

Humidity : 5 - 90 % relative air humidity (non-condensing)

Ambient temperature : 5 - 35 °C

BLUETOOTH VERSION & PROFILE

AVRCP (Audio Video Remote Control Profile) : Yes

A2DP (Advanced Audio Distribution Profile) : Yes

CONNECTIONS

Audio in/AUX in : Yes

IEC-Connector : Yes

Headphone connection jack (3,5mm) : 1

DECODER

Audio decoder : MPEG-1 & MPEG-2 layer I, II

DISPLAY

Type : OLED

FUNCTIONS

MP3 playback via USB : Yes

USB charging function : Yes

CD player with MP3 : Yes (mit Resume-Funktion)

HANDLING/COMFORT

Clock : Yes

Alarm : Yes

Snooze : Yes

LOUDSPEAKERS

Stereo speakers : Yes

Output performance : 20 W (RMS)

Stereo : 2 x 10 W

Equalizer : Yes

powered by ELAC : Yes

NETWORK & COMMUNICATION

Bluetooth : Yes

OTHER FEATURES

OSD languages : English, German, French, Italian

POWER SUPPLY

Nominal voltage : 230 V

Frequency : 50 Hz

Mains adapter : DC 12V / 3000 mA

Type of power supply : External

RADIO / RECEPTION

Aerial : DAB / FM telescopic antenna (replaceable)

RADIO TYPE

stationary radio : Yes

TUNER

Tuner type : Digital cable

DVB-C Tuner : 1

Cable radio : Yes

Reception on : DVB radio

TUNER - CABLE

Reception range : 50 ... 858 MHz

Demodulation : 64 / 256 QAM

Symbol rate : 2 ... 7 Mbaud

FEC : Reed-Solomon (204, 188)

SCOPE OF DELIVERY

CABLESTAR 400, power supply, user manual