



Philips  
Bluetooth party speaker

### Flashing party light

Wireless party link  
Rechargeable battery  
50 W RMS. 100 W max output



TAX4207

## Kick the party off

Raise the roof of any party with this brilliant party light cube speaker! Powerful sound, big bass and an awesome party light take the party to the next level. Connect up to 50 speakers for a wall of light and sound.

### Get the party started right

- Powerful sound with extra-heavy bass
- Party lights pulse and flash
- Connect easily via Bluetooth, USB or audio-in
- 2 x 2" tweeters and a 6.5" bass driver

### Rock the mic

- 2 mic inputs. Karaoke effects
- Echo, female/male voice switch and vocal fader effects
- Dynamic bass boost for rich, deep bass
- Pair for stereo and play it loud

### Shake the room

- Connect up to 50 speakers for a wall of sound
- 50 W RMS. 100 W max output power
- AC-powered. Built-in battery for 12 hours of play time
- Cube design with comfy handle. Dimensions: 30 x 31 x 30 cm

# PHILIPS

## Bluetooth party speaker

Flashing party light Wireless party link, Rechargeable battery, 50 W RMS. 100 W max output

# Specifications

### Sound

- Output power (RMS): 50 W
- Output power (MAX): 100 W
- Total harmonic distortion: 10%
- Frequency response: 40 Hz - 20 KHz,  $\pm 3$  dB
- Speaker impedance: Treble 8 ohm; Bass 4 ohm
- Sound enhancement: Dynamic Bass Boost

### Loudspeakers

- Number of sound channels: 2.1
- Driver configuration: 2-way
- Number of tweeters: 2
- Tweeter diameter: 2"
- Number of woofers: 1
- Woofer diameter: 6.5"

### Connectivity

- Mic in: 2 x (6.3 mm w/ vol control)
- USB: Type-A (playback, reading, service)
- Audio in: 1 x 3.5 mm
- Audio out: 1 x 3.5 mm
- Bluetooth: support SBC and AAC streaming
- Bluetooth version: 5.0
- Bluetooth profiles: Multipoint (Multipair) support, Music streaming (A2DP), Playback/volume control: AVRCP
- Bluetooth range: Line of sight, 30 m or 100 ft
- DLNA Standard: No
- Multiple speaker connection
- Multiple speaker scenario: Stereo, Broadcasting
- Multiple speaker technology: Wireless PartyLink, TWS
- Smart Home: None

### Supported Audio Formats

- Bluetooth: SBC, AAC
- USB: MP3, WAV, WMA, FLAC

### Convenience

- Karaoke: MIC volume, echo control, vocal fader,

voice changer

- Buttons and controls: Power on/off, Play/Pause, Volume up, Volume down, Lighting switch, Dynamic Bass Boost (DBB)
- Display screen: No
- Light Effect: Yes, speaker light effect, strobe light

### Compatibility

- Smartphone/tablet APP control: No

### Power

- Power supply: 100-240 VAC, 50/60 Hz
- Standby power consumption:  $\leq 0.5$  W
- Battery Type: Lithium-ion (built-in)
- Battery Capacity: 2200 mAh, 11.1 V
- Battery life time: 12 hr
- Charging time: 3 hr
- Power bank: No

### Accessories

- Included accessories: AC Power Cord, Quick start guide, Warranty certificate, Safety warranty sheet

### Product dimensions

- Product dimensions (W x H x D): 30 x 30.6 x 30 cm
- Weight: 5.94 kg

### Packaging dimensions

- EAN: 48 95229 12632 9
- Number of products included: 1
- Packaging type: Carton
- Type of shelf placement: Standing
- Packaging dimensions (W x H x D): 38.2 x 41.4 x 37 cm
- Gross weight: 7.7 kg
- Net weight: 6.035 kg
- Tare weight: 1.665 kg

TAX4207/10

# Highlights

### Extra bass. 12 hours of play time

This awesome karaoke cube speaker will bathe the room in rich sounds and banging bass. The built-in battery lets you take the party outside for up to 12 hours of play time on a single charge.

### Party lightshow

Flashing party lights on the front of the cube pulse and flash, creating a brilliant lightshow. The back light will change colour and pulse while the front light strobes.

### 2 Karaoke mic inputs

2 mic inputs let you add your voice to the party with karaoke mode. Kick it up with echo, a female/male voice switch and vocal fader voice effects. Both mics and effects have their own controls on the speaker.

### Bluetooth, USB and audio-in

Connect any way you like. Stream your tunes via Bluetooth. Easily connect other devices via audio-in or USB. You can also connect to another speaker or amp using the line-out socket.

### Wall of light and sound



You can connect up to 50 speakers together. A handle on the top and the cube design allow you to easily stack speakers on top of each other. Create a wall of sound and lights to get your party started right.



Issue date 2022-05-11

Version: 6.0.3

12 NC: 8670 001 82089  
EAN: 48 95229 12632 9

© 2022 Koninklijke Philips N.V.  
All Rights reserved.

Specifications are subject to change without notice.  
Trademarks are the property of Koninklijke Philips N.V.  
or their respective owners.

[www.philips.com](http://www.philips.com)