

## WiFi Smart Light Switch | Single

### General information

Traditional light switches just got a lot smarter. This Smart Wall Switch for Lights allows you to remotely and automatically take control of your lighting.

#### Easy to set up

The switch can be used to control your light by simply using the touch button on it. But, it also allows you to connect it directly to your Wi-Fi router and gain control of the light from your smartphone, tablet or by speaking, when used alongside Amazon Alexa or Google Home.

Note: Neutral wire required to always power the switch with 230 Volts

#### Schedule and pair

The intuitive app that provides the brains behind this Smart Wall Switch for Lights allows you to pair this light to other appliances to create the perfect ambient setting in your room with just one command or set the light to turn on automatically - ideal if you are going to be away for a few days.

#### Discrete

The sleek and easy-to-clean glass front blends into your interior, and yet this discrete unit is powerful enough to support electrical lights of up to 300 W.

#### About Nedis® SmartLife

Discover a wide and ever-expanding range of products - such as bulbs, switches, sockets, sensors, and cameras - that can all be controlled through an easy-to-use and intuitive app. With voice control features supported by Amazon Alexa and Google Home, and no need for anything more than your existing Wi-Fi network, this is the connected, smart home made simple. Whether you're looking for a single smart bulb or socket, or you want to automate your entire house, discover how accessible smart technology is today.



### Sales information

Order code: **WIFIWS10WT**  
Product description: WiFi Smart Light Switch | Single  
Packaging: Giftbox with eurolock  
Brand name: Nedis



Quantity	LxWxH (mm)	Weight
1	105x125x50	150 gr.
50	280x280x555	9500 gr.

## WiFi Smart Light Switch | Single

### Features

- Durable - offers a lifetime of over 100,000 switch cycles
- Discrete - blends into your room's interior
- Powerful - allows you to schedule lighting, pair with other appliances and devices, and control with your voice (with Amazon Alexa or Google Home)
- Versatile - can be operated locally as a traditional wall light switch or remotely and automatically

### Specifications

Operating temperature:	-20 - 50 °C
Maximum radio transmit power:	19 dBm
Antenna gain:	2 dBi
Frequency range:	2412 - 2462 MHz
Internal depth:	25 mm
Hole spacing, mounting plate:	60 mm
Width:	86 mm
Height:	86 mm
Dimensions (Calculated):	10 mm (L) x 86 mm (W) x 86 mm (H)
Mounting:	Wall Mounting
Programming functions:	Switch On
Programming functions:	Switch Off
Programming functions:	Switch On with Time Delay
Programming functions:	Switch Off with Time Delay
Programming functions:	Button
App available for:	Android™ & iOS
Compatible with:	Nedis® SmartLife
Input voltage:	100 - 240 VAC 50 Hz
Number of outputs:	1
Colour:	White
Material:	Glass
Maximum power output:	300 W
Wireless technology:	Wi-Fi
Length:	10 mm



---

## WiFi Smart Light Switch | Single

### Package contents

Smart wall switch  
Quick start guide