

Radio CXT® / LXT® / XGT®

MR007G

12V - 40Vmax

With Bluetooth. Dual Power Sources: AC or Makita batteries.

MR007G The subwoofer on the bottom & the midrange/treble speakers on both sides provide deeper & richer high quality sound to suit various music genres. MY EQ (my equalizer) mode enables to independently adjust treble, midrange and bass for a desired sound quality. DAB/DAB+ (Digital Audio Broadcasting)



Technical specifications

Nominal Battery Voltage	12 / 14,4 / 18 / 40 V
CXT Battery	✓
Voltage LXT	✓
Voltage XGT	✓
Frequency Range FM	87,5 - 108 MHz
Frequency Range DAB+	174,928 - 239,200 MHz
Continuous Use 18V / 6.0 Ah Battery	20 h
International Protection Class (IP)	IP65
Tool weight with battery (EPTA)	5,5 - 6,3 kg
Product Dimensions (L x W x H):	285 x 172 x 305 mm
Continuous Use 18V / 3.0 Ah Battery	9,5 h
Bluetooth	✓
Battery Chemistry (Ni-Cd / Ni-MH / Li-ion)	Li-ion
Speaker Output Power 12Vmax	2 W (x2) + 10 W
Speaker Output Power 18V	5 W (x2) + 25 W
Speaker Output Power 40Vmax	5 W (x2) + 25 W

User benefits

- Equipped with equaliser for 7 selectable sound modes
- Sound mode can be selected to suit the music genre
- LED colour indicates the selected sound mode
- Equipped with Bluetooth to wirelessly connect your mobile device to play music
- IP65 rated for maximum weather and water resistance
- Battery protection circuit protects against overloading, over-discharging and over-heating

Link to product - www.makita.com



Related products

■ Other

User manual

Parts drawing